

ZSI overview table

Date: 05-10-2020

	Available ZSI terminals
A:	Z1, Z2
B:	Z1, Z2, Z3, Z4
C:	Z1, Z2, Z3, Z4, Z5

Z1-Z5 zone selective interlocking:
 Z1 = ZSI OUT SOURCE
 Z2 = ZSI OUT ; Z3 = ZSI IN SOURCE
 Z4 = ZSI IN ST (short time)
 Z5 = ZSI IN GF (earth fault)

Circuit breakers >	NSX100-250	NSX400-630	NS630b-1600	NS1600b-3200	NT	NW	MTZ
Trip Units							
Micrologic 2.2	-						
Micrologic 2.2M	-						
Micrologic 4.2	-						
Micrologic 5.2A/E	A						
Micrologic 6.2E-M	A						
Micrologic 7.2E	-						
Micrologic 2.3		-					
Micrologic 1.3M		-					
Micrologic 2.3M		-					
Micrologic 4.3		-					
Micrologic 5.3A/E		B					
Micrologic 6.3E		C					
Micrologic 6.3E-M		C					
Micrologic 7.3E		-					
Micrologic 2.0			-	-	-	-	
Micrologic 5.0			-	-	-	-	
Micrologic 6.0			-	-	-	-	
Micrologic 2.0A			-	-	-	-	
Micrologic 5.0A			B	B	B	B	
Micrologic 6.0A			C	C	C	C	
Micrologic 7.0A			B	B	B	B	
Micrologic 2.0E			-	-	-	-	
Micrologic 5.0E			B	B	B	B	
Micrologic 6.0E			C	C	C	C	
Micrologic 5.0P			B	B	B	B	
Micrologic 6.0P			C	C	C	C	
Micrologic 7.0P			B	B	B	B	
Micrologic 5.0H					B	B	
Micrologic 6.0H					C	C	
Micrologic 7.0H					B	B	
Micrologic 2.0X							-
Micrologic 5.0X							B
Micrologic 6.0X							C
Micrologic 7.0X							B

	Available ZSI terminals
A:	Z1, Z2
B:	Z1, Z2, Z3, Z4
C:	Z1, Z2, Z3, Z4, Z5

Z1-Z5 zone selective interlocking:
 Z1 = ZSI OUT SOURCE
 Z2 = ZSI OUT ; Z3 = ZSI IN SOURCE
 Z4 = ZSI IN ST (short time)
 Z5 = ZSI IN GF (earth fault)

Done by: Lars Skovly & Thordur Svanbergsson